

# Z8 Portable Plug-n-Play 4G Camcorder

## Overview

Congratulations on your purchase of Z8 Portable Plug-n-Play 4G Camcorder! The Z8 requires no setup and installation. It uses 4G data cellular network for real-time surveillance and is able to record video and audio on the microSD card locally. You can use the smartphone to access Z8 anytime anywhere.

Z8 has a built-in rechargeable battery which can operate up to 5 hours. Use the app "UBox" to configure the features on Android / iOS smartphone.

## Features

**Loopback Recording** – Overwrite recordings once memory card is full

**Photo-taking** – Capture photo to smartphone

**Record to phone** – Record video to smartphone

**Simultaneous Operation** – Z8 can operate when it is charging

**Support max 128GB microSD (TF) card** – Please visit [www.atteztech.com](http://www.atteztech.com)-> Support-> Knowledge Base for details.

**Sharing** - You can invite another user to connect to Z8 by sharing the camera QR code

## Smartphone Requirement

Android 10 or later, iOS 14 or later version

## Charging

Z8 comes with an internal rechargeable battery. It can be charged by connecting to the USB port of a PC or power bank or 5V DC adapter. If it is the first time using Z8 or Z8 is not used for a long period, please charge the battery for 2 hours before use.

## Status

### Charging LED

Green: charging

LED off: charging completed

### Status LED

#### Power on / off Z8

On: Put the slide switch to the ON position, the blue and red LED is on

Off: Put the slide switch to the OFF position, the LED is off

Remark: Power off the camera before

inserting or removing the cards

### Operating

**1a.** Connecting to 4G network

Blue LED flashes slowly

**1b.** No SIM card

Blue LED flashes fast

**1c.** Connected to 4G network

Blue LED steady on

**2.** Restore to default

Blue and red light will be off then on again

## Setup

Step 1: Install the app "Ubox"

Android / iPhone / iPad:

Go to App Store, search "Ubox", and install the app

1.1 Go to the app "Ubox"

1.2 Press "Register" and create a new account if you do not have an account before. Otherwise, simply login with your existing account. Please enter LETTER and NUMBER only for the account name and password.

Step 2: Add new device

2.1 Press + at the upper right corner

2.2 When the app asks for particular permissions, please go to phone settings to grant the permissions, or just press "I got it" if permission is granted already

2.3 Scan the camera UID barcode, or press "... " at the upper right corner

2.4 Select "Add manually" and enter the camera UID

Step 3: Live view

Insert a 4G SIM card (with gold contact facing up) into the SIM card slot and turn on Z8. After a while, you can watch the liveview in the app

Step 4: Watch files recorded on the microSD card

Insert a microSD card into the microSD card slot. Press "Playback" and select "TF card" to watch the files recorded on microSD card

Step 5: Push notification message

Press "Messages" for the list of push notification.

## Frequently Asked Question (FAQ)

**Q1: What to do when Z8 does not respond?**

Turn OFF and then ON the Z8

**Q2: Why cannot connect to Z8?**

Maybe Z8 is turned off: Turn it on again;

Maybe Z8 has error or has no response: Please power cycle the Z8;

If blue LED is flashing: The camera cannot connect to the 4G network, please ensure the SIM card is inserted properly and it has data service

The Z8 is configured to "Super power saving mode", it can only be woke up by radar trigger, but not by the app. In Power mode, change to "Power saving mode" or "Continuous working mode"

**Q3: How to reset to factory default?**

While Z8 is powered on, press and hold the RESET key until the blue and red LED is off and then on again (for around 15 seconds)

**Q4: What is the recorded file format and size on microSD card?**

Video format: .mp4 Size: HD(1920x1080p) Approximate 0.5GB / hour

**Q5: Why is there no recording on Z8?**

The Z8 is not turned on;

OR, there is no microSD card / card is full / card is damaged, please use another FAT32 formatted microSD card.

**Q6: Why is the streaming video not smooth?**

Maybe the network speed is too slow, please change to "SD" in live view.

**Q7: Why does the PC not able to read the SD card?**

Please make sure Z8 is turned off and take out the card and insert the card into a card reader and connect the card reader to the PC. The Z8 cannot act as a removable drive when connecting to the PC.

**Tips of Use**

1. If you cannot connect Z8 for a long time, please close the app or force to stop the app and run the app again. Reboot Z8 if needed also.
2. Optimal operating temperature is 32°F to 113°F (0°C to 45°C). Z8 cannot be exposed directly under sunlight.
3. Please use a FAT32-formatted microSD (TF) card. For details, please visit [www.atteztech.com](http://www.atteztech.com) -> Support -> Knowledge Base.
4. Do not put the camera close to the smartphone to reduce interference.

**Warranty: 12 month**